

2015-2020 Ford F-150 | Easy | 10 minutes | \$0 DIY

TOOLS

Jumper cables or portable jump pack

STEPS

- 1 Position the vehicles - Park the good vehicle close enough for the cables to reach both batteries, but do not let the vehicles touch. Turn off both engines and all accessories.**
- 2 Connect red to dead positive - Connect one end of the red cable to the positive (+) terminal of the dead battery.**
- 3 Connect red to good positive - Connect the other end of the red cable to the positive (+) terminal of the good battery.**
- 4 Connect black to good negative - Connect one end of the black cable to the negative (-) terminal of the good battery.**
- 5 Connect black to ground on dead car - Connect the other end of the black cable to a clean, bare metal ground on the dead car's engine block - not the negative terminal. This reduces spark risk near the battery.**
- 6 Start and remove in reverse - Start the good car, wait a minute, then start the dead car.** Let it run for several minutes. Remove cables in the reverse order: black from ground, black from good, red from good, red from dead.