

2018-2024 Jeep Wrangler | Easy | 20 minutes | \$150 DIY

TOOLS

Wrench set Battery terminal cleaner
Safety glasses Wire brush

PARTS

Group-size battery (match your tray)
\$140.00

STEPS

- 1 Prepare the vehicle - Power windows down, radio code noted if needed, hood open, eye protection on.** Note any IBS (battery monitoring) sensor on the negative cable.
- 2 Disconnect negative first - Loosen and remove the negative (-) terminal first, then the positive (+).** This prevents shorting if your wrench touches the body.
- 3 Remove the hold-down - Remove the battery hold-down clamp or J-clamp.** Note the group size and terminal orientation before lifting the battery out.
- 4 Clean the tray - Clean the tray and terminal posts with a wire brush and terminal cleaner.** Inspect the cables for corrosion or damage.
- 5 Install new battery - Place the new battery matching group size and terminal type.** Secure the hold-down. Connect positive (+) first, then negative (-).
- 6 Reset if required - Register or reset the battery monitoring system if the manual or a scan tool says to.** Some vehicles learn the new battery's current draw.