

2019-2024 Volkswagen Jetta | Easy | 10 minutes | \$0 DIY

TOOLS

Jumper cables or portable jump pack

STEPS

- 1 Position the vehicles - Park the good vehicle close enough for the cables to reach both batteries, but do not let the vehicles touch. Turn off both engines and all accessories.**
- 2 Connect red to dead positive - Connect one end of the red cable to the positive (+) terminal of the dead battery. The positive terminal is usually marked with a plus or red cover.**
- 3 Connect red to good positive - Connect the other end of the red cable to the positive (+) terminal of the good battery.**
- 4 Connect black to good negative, then to ground - Connect one black clamp to the good battery's negative (-) terminal. Connect the other black clamp to a clean, bare metal ground on the dead car's engine block - not the negative terminal.**
- 5 Start and remove in reverse - Start the good car, wait a minute, then start the dead car.** Let it run several minutes. Remove cables in reverse: black from ground, black from good, red from good, red from dead.